Elso Philips Service; tel: +421 32 6582410 email: elso@elso.sk; web: www.elso.sk

EXELIS APPLIED KILOVOLTS

HV Lab Series 477 Data Sheet

±500V, ±1kV, ±2kV, ±3kV **4W HIGH VOLTAGE LAB POWER SUPPLY**

Application:

Photomultiplier, mass spectrometers, nuclear and medical instrumentation.

- ±0.5kV, ±1kV ±2kV, ±3kV versions
- Input 230 / 115VAC
- Switchable output polarity
- Remote voltage programming or potentiometer setting
- Very low ripple and noise
- Direct reading meter for voltage & current



Electrical Specification

Order Code	Polarity	Output Voltage	Output Current	Ripple pk-pk	Input Voltage
477-301	Switchable	±500V	8mA	5mV	115V / 230V ac
477-302	Switchable	±1kV	4mA	4mV	115V / 230V ac
477-303	Switchable	±2kV	2mA	2mV	115V / 230V ac
477-304	Switchable	±3kV	1.3mA	5mV	115V / 230V ac

Input	115/230V ac nominal, \pm 10%, 50/60Hz (Switchable 2 ranges). 35VA rating at full load.
Line regulation:	<20ppm over input voltage range.
Load regulation:	<20ppm for zero to full load.
Drift (after 1 hour warm up)	<15ppm in any 15 minute period, <50ppm in any 8 hour period.
Temperature coefficient	<50ppm / °C at maximum rated output.
Control of output (Local)	Front panel 10 turn potentiometer with locking vernier calibration.
Control of output (Remote)	0 to +10V for 0 to 100% rated output voltage, input Z = 10k.
Voltage rate of change limit	Selectable from the front panel, ("Ramp"), this limits the rate of change to <2V/mS (at max voltage) reducing the possibility of arcing within the load application or PM tube.
Protection	Current is limited to approximately 110% of maximum rated output until overload condition is removed. Protected against intermittent flashover to ground.
Voltage & current monitor	Direct reading 4½ digit meter, switch selectable between output current and voltage. Available also are buff- ered monitor outputs for both current and voltage (available from the analogue port on the rear panel, 0 to +10V corresponds to 0 to 100% of the rated output) Accuracy: Voltage 1%. Current =2%.
Auxiliary output	Fixed \pm 5V and \pm 15V dc @ 250mA, regulation : \pm 1%, ripple 10mV pk-pk.
Reference output	+10V.0V \pm 0.05%, temperature coefficient : <50ppm / °C.

http://www.elso.sk/product.php?id_product=3235

Environmental Specification

Temperature, operating

-10 to +50°C. De-rate above 35°C linearly to 80% power at 50°C.

Temperature, storage

Pollution category

Humidity (RH) <31°C

Humidity (RH) >30°C

80% maximum non-condensing Decrease linearly to 50% at 40°C

254 212.73 brandenburg Photomultipler Power Supply v O Output HHHF IO Ō'n Voltage Adjust 98.88 Local Mode 🖬 🖊 📓 ON/OFF ON/OFF Function Meter Control Ramp Polarity Output Aux O/P Ô 0 0 0 Ground Output Mains 9 m 254.0

-20 to +75°C.

Ш

Mechanical Specification

Dimensions	W x H x D: 254 x 109 x 254 mm, inc feet & handle. (10" x 4.25" x 10.0")
Weight	4kg (9lb) approximately.
Input	IEC mains connector on rear panel.
Control	9 way "D" type on rear panel.
HV Output	2 off HV SHV connectors on front panel.
Aux output	Binder 680 series, 7 pins, on front panel.

Pin Assignments

Control (rear) connector pin assignments

Pin 1	N/C
Pin 2	Control input
Pin 3	Current monitor
Pin 4	Voltage monitor
Pin 5	N/C
Pin 6	N/C
Pin 7	Reference output
Pin 8	Signal ground
Pin 9	N/C

Aux (front) connector pin assignments

Pin 1	-15V
Pin 2	-5V
Pin 3	0V
Pin 4	+5V
Pin 5	0V
Pin 6	+15V
Pin 7	0V

EXELIS

Applied Kilovolts Ltd

(a subsidiary of Exelis Inc) Exelis - Power Solutions, 11 Interstate Drive, West Springfield MA 01089 Tel: 1 413 263 6204/6360 Fax: 1 413 737 0608 Web: www.exelis-ps.com E-mail: psinfo@exelisinc.com

Applied Kilovolts Ltd

(a subsidiary of Exelis Inc) Woods Way, Goring by Sea, BN12 4QY. United Kingdom. Tel: +44 (0) 1903 708 850 Fax: +44 (0) 1903 708 851 Web: www.exelis-ps.com E-mail: sales@appliedkilovolts.com

Exelis is a trademark of Exelis Inc.

Copyright © 2013, Exelis Inc. All rights reserved.